

2- and 4-Port Multimedia KVM Switches

Signamax Connectivity Systems' CommandView KVM switch is a high performance yet low cost console (Keyboard, Mouse, Monitor, Speaker and Microphone) sharing switch for IBM compatible PCs. You can control any 2 or 4 PS/2 style PCs with only one set of Keyboard, Mouse, Monitor and Headset console devices.

Designed with Plug and Play function and fully emulation of keyboard and mouse response including Wrap (Echo) mode, more innovative features added to help you work on different platforms and switch smoothly among them. Now, you can share your console devices with Notebook computer and desktop PC.

It is compact, easy to install, and doesn't need any external power adapter. Moreover, NO extra software is required to install, and hence there are no software incompatibility problems to worry about.



Model 098-8120 rear panel



Model 098-8120



Model 098-8140

2- and 4-Port KVM Switches

PART NO.	DESCRIPTION
098-8120	Multimedia 2 port KVM Switch, Desktop, with Mic. & Audio
098-8140	Multimedia 4 port KVM Switch, Desktop, with Mic. & Audio

FEATURES

- Access 2 or 4 computers with one set of keyboard, mouse, monitor and headset.
- An innovated Broadcast mode will turn your keyboard strokes and mouse movements broadcast to all computers at the same time. That is useful when you operate the same activities on all identical computers, such as configuration, OS installation.
- A built-in 3.9V voltage detector will stop activity when cabling is too long or the load of console keyboard and mouse is too heavy.
- Supports PC-AT and PS/2 keyboard (AT requires an AT-PS/2 adapter).
- Supports Microsoft IntelliMouse Explorer (5 key+Wheel), Microsoft IntelliMouse (3 Key+Wheel), Logitech MouseMan+, FirstMouse+, and IBM Scroll Point Mouse.
- Designed for Plug-and-Play operation.
- Full emulation of Keyboard and Mouse for all inactive channels; Now, you can boot up PC even without keyboard and mouse installed on the switch.
- The status of keyboard's Caps Lock, Num Lock, Scroll Lock and typematic rate are automatically saved and restored when switching among computers.
- Supports simple cascade up to 4 stages by setting different Hot-key on each stage.
- Supports resolution from VGA, SVGA and up to (2,048 x 1,536 @ 75 Hz).
- VGA amplifier bandwidth is 300 Mhz, Av = 1 for a crystal clear video output.
- Supports VESA DDC1/2B standard.
- 3 kinds of PC selection method: by keyboard number keys, arrow-keys and push button.
- A wheel mouse can be set to different mode (with wheel or without wheel) for different PC OS.
- The moving speed of mouse can be set to Fast or Slow.
- Hardware reset can be activated by Hot-key command or press push button for more than 5 seconds.
- Two Scan modes: Automatically switches through powered-on computers or stop on each computer.
- Total 8 time intervals can be set for Scan mode: 4, 5, 10, 15, 20, 25, 40, 60 seconds.
- Keyboard's LED will flash to indicate the scan time interval setting by binary form in Hot-key mode.
- Keyboard and mouse activity can be Locked and Unlock.
- Audio I/O can be locked to particular channel.
- Built-in Keep-Alive feature will allow Keyboard and Mouse remove and attach again.
- A sophisticated Hot-key command set will help user to extend the usage of KVM switch without power-down to change console devices.
- Uses Combo KVM+Audio cable for easy installation and also prevent from cable tangling, cross-plugging.
- Small size and easy to install and operate.
- No software required.
- No external power required. An optional power jack reserved for long distance cabling